

1. TRANSMITTED DATA

1-1 CHANNEL MESSAGES

[H]:Hex, [D]:Decimal

Status [Hex]	Second [H] [D]	Third [H] [D]	Description
8n	kk (kk)	40 (64)	Note Off
9n	kk (kk)	vv (vv)	Note On (vv = 1~127)
Bn	40 (64)	00/7F (0/127)	Damper Pedal
Bn	42 (66)	00/7F (0/127)	Sostenuto Off/On
Bn	43 (67)	00/7F (0/127)	Soft Pedal
Bn	7B(123)	00 (0)	All Note Off
Cn	pp (pp)	-- --	Program Change (pp = 0,4,6,11,19,48)

n : MIDI Channel (0~15)

vv: Value

1-2 SYSTEM REALTIME MESSAGES

Status[H]	Description
FE	Active Sensing

2. RECOGNIZED RECEIVE DATA

2-1 CHANNEL MESSAGES

Status [Hex]	Second [H] [D]	Third [H] [D]	Description
8n	kk (kk)	vv (vv)	Note Off (vv = 0~127)
9n	kk (kk)	00 (00)	Note Off
9n	kk (kk)	vv (vv)	Note On (vv = 1~127)
Bn	40 (64)	vv (vv)	Damper Pedal
Bn	42 (66)	vv (vv)	Sostenuto Off/On
Bn	43 (67)	vv (vv)	Soft Pedal
Bn	7A(122)	00/7F (0/127)	Local Control Off/On
Bn	7B(123)	00 (0)	All Note Off
Cn	pp (pp)	-- --	Program Change (pp = 0,4,6,11,19,48)

n : MIDI Channel No.(0~15)

vv: Value

2-2 SYSTEM REALTIME MESSAGES

Status[H]	Description
FE	Active Sensing